

Release Note Quadro2x 5.2.9, Edition 1

THIS DOCUMENT CONTAINS CONFIDENTIAL AND PROPRIETARY INFORMATION OWNED BY EPYGI TECHNOLOGIES LTD. ANY COPYING, USE OR DISCLOSURE OF THE DOCUMENT OR THE INFORMATION CONTAINED HEREIN WITHOUT THE WRITTEN PERMISSION OF EPYGI TECHNOLOGIES LTD. IS STRICTLY PROHIBITED.

1 Introduction

This Release Note describes hardware and software requirements to use with the

Quadro2x software 5.2.9 Date: May 25, 2010

Additional enhancements, bug fixes and known issues incorporated in this software will be listed as known.

Date: June 2, 2010

2 Requirements

2.1 Hardware requirements

Attention: The 5.2.x software can be used on almost all Quadro2x units. The exception to this is for older Quadro2x models that have only 32MB of NAND flash memory. The following hardware versions support 5.2.x: SASY-MICRO-0101-0002, SASY-MICRO-0101-0101, SASY-MICRO-0102-xxxx, SASY-MICRO-0103-xxxx

Additional details are provided in **Section 7: Upgrading Instructions**

2.2 Software requirements

Attention: The software upgrade to 5.2.x can **ONLY** be done from 5.1.38 and higher 5.1 versions. Before updating to 5.2.9 the unit should be updated to 5.1.38 or higher 5.1 version first.

2.3 Supported and Tested SIP phones

Below is the list of SIP phones with the corresponding firmware versions that are supported by Epygi and are recommended for optimal compatibility with Quadro2x.

Vendor	Model	Software
SNOM	300	Application: snom300-SIP 7.3.27
SNOM	320	Application: snom320-SIP 7.3.27
SNOM	360	Application: snom360-SIP 7.3.27
SNOM	370	Application: snom370-SIP 7.3.27
SNOM	820	Application: snom820-SIP 8.2.11
SNOM	870	Application: snom870-SIP 8.3.2
SNOM	MeetingPoint	Application: snomMP-SIP 8.2.1
Aastra	480i	Application version: 1.4.3.23
Aastra	9112i	Application version: 1.4.3.23
Aastra	9133i	Application version: 1.4.3.23
Aastra	9143i (33i)	Application version: 2.5.2.1010
Aastra	9480i (35i)	Application version: 2.5.2.1010
Aastra	6751i	Application version: 2.5.2.1010
Aastra	6753i	Application version: 2.5.2.1010
Aastra	6755i	Application version: 2.5.2.1010
Aastra	6757i	Application version: 2.5.2.1010
Aastra	6730i	Application version: 2.5.2.1010
Aastra	6731i	Application version: 2.5.2.1010

Please Note: Any problems and limitations on the SIP phones listed below are described in detail in the **Quadro Features on Supported IP Phones** document.

Please Note: Quadro IP phones firmware control mechanism will not upgrade Snom firmware version from 6.x to 7.x. This should be done manually via Snom web site. Once the Snom firmware version is 7.x, the Quadro's firmware control will automatically upgrade/downgrade the phone to Epygi's recommended version but not to 6.x.

In the list below are the SIP phones with the corresponding firmware versions that are tested by Epygi. The document **Quadro Features on Tested IP Phones** describes the problems and limitations on the SIP phones that have been tested by Epygi.

Vendor	Model	Software
CISCO	7960	POS3-07-4.00
IpDialog	ST201	Application: SipTone 1.2.0 rc Z_21
POLYCOM	SoundPoint IP 300SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 330SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 331SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 335SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 450SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 501SIP	Application: SIP software 3.1.1.0137
POLYCOM	SoundPoint IP 601SIP	Application: SIP software 3.1.1.0137
POLYCOM	SoundPoint IP 550 SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundPoint IP 650 SIP	Application: SIP software 3.2.2.0477
POLYCOM	SoundStation IP 6000	Application: SIP software 3.2.2.0477
POLYCOM	VVX 1500	Application: SIP software 3.2.2.0481
SIPUra	SPA 841	3.1.4(a)
Snom	M3	Application: snom-m3-SIP 01.16
Snom	190	Application: snom190-SIP 3.60s

Vendor	Model	Software
Snom	200	Application version: 3.56m
Snom	220	Application version: 3.56m
Swissvoice	IP 10S	Application version: IP10 SP v1.0.1 b3
Thomson	ST 2030 SIP	APP Version: V1.57
Berkshire (ATL)	5000	SW version: 22102154
Grandstream	BT200	Program- 1.1.6.16
Grandstream	BT100	Program- 1.1.0.3
Grandstream	GXP2000	Program- 1.1.6.16
Linksys	SPA921	SW version: 5.1.8
Linksys	SPA922	SW version: 5.2.8
Linksys	SPA941	SW version: 5.1.8
Linksys	SPA942	SW version: 5.2.8
Yealink	T20	SW version: 9.43.0.30
Yealink	T22	SW version: 7.43.0.30
Yealink	T26	SW version: 6.43.0.30
Yealink	T28	SW version: 2.43.0.30
Aastra	MBU400	Application version: 1.0.8
Telematrix	IP550 Spectrum Plus	SW version: 1.7.252.253
Telematrix	3300IP	SW version: 1.7.249.248

Both mentioned documents are available at www.epygi.com and can be found under the Channel's Portal.

2.4 Interaction with other Quadro SW releases

QuadroISDN or QuadroFXO external PSTN gateways used in the shared mode should have SW 5.1.12 or higher to achieve maximum feature functionality with the Quadro2x 5.2.9.

QuadroFXS 16 Gateway should have SW 5.2.1 or higher for PnP configuration with the Quadro2x SW 5.2.9.

ActiveX Control SW 5.1.1 or higher should be used with 3pCC functions with the Quadro2x 5.2.9.

3 New Features History

The table below indicates a high-level list of new features that have been added beginning with the most recent Quadro2x release.

Release	New Features
5.2.9	<p>Full support for Secure RTP (SRTP) to encrypt voice packets.</p> <p>Full support for TLS (Transport Layer Security) protocol (RFC 2246) to provide communications privacy for the SIP messaging port over the Internet. The protocol allows client/server applications to communicate in a way that is designed to prevent eavesdropping of the SIP messages.</p> <p>HD codecs such as G.722 and G.722.1 are now supported in pass-through mode.</p> <p>Security enhancement. Password strength checking has been added in the IP Lines settings table for configuring IP Phones. The system will provide feedback on whether the chosen password is weak. An option is also provided to let the system create a strong, random password. Password strength enforcement can be configured in the hidden menu <code>generalconfig.cgi</code>.</p> <p>Security enhancement. Protection against certain SIP DoS attacks has been added by enabling the "SIP IDS" feature in the hidden menu <code>generalconfig.cgi</code>. Enabling this option will automatically block malicious IPs in the firewall.</p> <p>Global speed dialing. Configured in Telephony/Call Routing/Global Speed Dial Directory. An Excel .CSV file can be used to upload the entries in the format: Code, Number (e.g. 44, 9726921166). Each entry should be on a new line.</p> <p>Emergency Call Interrupt feature in the Caller ID based services. A new feature that will allow specific Caller Ids to be configured so that a call received from one of these numbers will immediately disconnect the call in progress and ring the user's extension.</p> <p>Configuring IP phones from WAN option</p> <p>System logging enhancement. If a user encounters a problem while on a phone call the pertinent details related to the call can be saved. The user will dial *82 (getting dialtone and dial *82 from the same or a different phone) as soon as the problem occurs. The details will be saved until the next time someone enters *82. When the <code>systemlogs</code> are downloaded it will contain the details from the most recent *82 entry.</p> <p>The voicemail to email option can now be configured in Telephony/Voice Mail Common Settings so that the subject of the email contains a user defined text along with selected system variables (e.g. caller id).</p> <p>Option to select the format of FAX in Voice Mail sent by email. Defined in Telephony/Voice Mail Common Settings. TIFF or PDF can be used.</p> <p>A prompt to the user is provided with the option to save the system configuration prior to executing a firmware update</p> <p>Authorized phones database can now be used with a custom auto attendant scenario. This allows callers to bypass authentication in custom auto attendants for user's who have been included in the authorized phone database.</p> <p>Configurable auto attendant Callback Response Delay allows users to specify a timeout before the system will try to call back the user.</p> <p>Configurable auto attendant callback activation timeout from the GUI, which allows activating automatic Call Back for trusted PSTN and SIP callers not after the one - two rings as previously defined, but during the time frame specified in the GUI. So now users can configure the activation timeout in seconds needed to wait for initiating the callback. This configuration is accessible from the hidden menu <code>"extmanagement.cgi"</code>.</p>

Release	New Features
	<p>Allow the Automatic Callback feature to be used to call back to the originating caller using the "Auto" call type. User can select "Auto" as the "Callback Call Type", while leaving the "Callback Destination" field empty. This will allow to callback to the caller using the Caller ID for callback.</p> <p>Quadro FXS gateway PnP support</p> <p>Full VLAN support for IP Phones (multiple subnets/DHCP)</p> <p>Support for T38 FAX proxy (from standalone IP Phone in the LAN to outside)</p> <p>Yealink IP phone enhancements. PnP and auto configuration support for T20, T22 and T26 models. Advanced button configuration added in the IP Line Settings. Receptionist configuration support for add on modules. A custom logo image can now be displayed.</p> <p>Polycom IP phone enhancements. PnP and auto configuration for Polycom IP335 and IP450 models. Advanced button configuration added in the IP Line Settings. Receptionist configuration support for add on modules. Custom data files for Polycom IP phones can now be uploaded from the hidden menu <code>ipphonesdirectory.cgi</code>.</p> <p>PnP and auto configuration for Aastra 6730i phone</p> <p>PnP and auto configuration for snom 870 and snom MeetingPoint</p>
5.1.39	
5.1.38	<p>Ability to configure speed-dial buttons of Snom IP phones via IP phone template mechanism</p> <p>The size of NAND Flash memory is shown in the HW status page</p>
5.1.31	Possibility to download the call statistics in CSV format
5.1.27	<p>Telematrix IP phones auto configuration support</p> <p>Call Forking (FindMe/FollowMe service)</p> <p>Call max duration (disconnecting call after specified time)</p> <p>Yealink phone auto configuration</p> <p>Reason header in SIP CANCEL message (prevents the call from being reported as "missed" if it was picked up by another extension)</p> <p>Auto configuration and compatibility for Polycom VVX 1500 video phone</p> <p>Automatic logout for HotDesking phones</p> <p>Hot Desking capability enabled for remote extensions</p> <p>Line appearance added on Remote Extensions</p> <p>Park slot segmentation (access list for call parking and retrieve)</p> <p>3PCC: capability for 3pcc programmer to modify username</p> <p>Shared Voice Mailbox</p>

Release	New Features
	<p>Call routing table debug/tracing tools (new events raised from Routing rule: call failover, fail, success)</p> <p>Aastra 6731i autoconfiguration and PnP</p> <p>Polycom Soundpoint IP 331 auto configuration and PnP</p> <p>3PCC: ability to differentiate call failure reasons (different error codes)</p>
5.1.19	
5.1.18	
5.1.17	<p>Music on Hold can originate from the Epygi Media Streamer which is a software application running on a PC that can have a playlist of MP3 files.</p> <p>The Quadro Call Statistics (CDR) can be automatically sent via email or uploaded to an FTP or TFTP server.</p> <p>Plug and Play for Polycom IP Phones</p> <p>Click To Dial (CTD) feature updated to allow calls to be initiated from a Website, connecting two parties together via the Quadro. There are two options to make the call:</p> <p>(a) Using the HTTP request to specific URI from a third party WEB page or application;</p> <p>(b) Using a special hidden page on Quadro's WebGUI (in the hidden menu callcontrol.cgi)</p> <p>New system events added to track IP phones registration status</p> <p>A custom logo image can be displayed on SNOM 360, 370 and 820 IP Phones</p> <p>Speed Dial numbers can now be updated from the phone handset (*76)</p> <p>Outgoing Call Blocking can be updated from the phone handset (*79)</p> <p>Hot Desking feature. This allows a single phone (IP or analogue phone) to be used by many users. Users can login to the Hot Desking phone (*78) using their extension number, and get all the credentials of their extension until they logout (*78).</p> <p>Virtual extensions can be optioned to provide a simulated ring back. The VE can be assigned to a receptionist phone and this option will now give him/her the option to answer the call before it goes to voice mail.</p> <p>Zero-out on Auto Attendant</p> <p>The Automatic Call Back option has been expanded to include callback to SIP callers. Previously, this feature was specific to PSTN callers.</p> <p>TLS/SSIP support added to send and receive encrypted SIP messages from designated peers</p> <p>Video phone support (proxy mode)</p> <p>E1 MELCAS digital hookflash feature added for E1 CAS to SIP calls</p> <p>The Unconditional Call Forwarding option has been enhanced so that enabling/disabling the feature from the handset can include the designated caller Ids.</p> <p>Load balancing for the FXO lines (including FXO gateways)</p>

Release	New Features
	Easier for extensions to forward their calls to external numbers without compromising the security of Call Routing entries that have the PBX filtering option enabled.
	Possibility for a user to designate a bad call in the system logs by dialing *81 after releasing the bad call.
	The Quadro system voice messages can be browsed and updated from a PC using 3PCC
	New features in 3pcc: Using the SIP Dialog package the call states for extensions can be viewed and tracked.
	New features in 3pcc: This feature allows the 3pcc application to subscribe to the Quadro's extension's list and receive an event notification the list has changed.
	New features in 3pcc: The connect function has been added which allows the application to use an extension's authentication parameters (extension number, password). After successful connection establishment an application can manipulate options on the extension.
	New features in 3pcc: Capability to upload the contents of legible configuration files and do the configuration update via 3pCC
	An option to "Discard Non-Numeric Symbols" is added in the Call Routing Wizard to delete extra characters that might be received in the caller id.
	Possibility to append the called number to the caller id using the format <dialnum:range>. This will allow the user to appropriately answer a call based on the number that was dialed.
	Snom M3 support
	Snom820 auto-configuration support
	Ability to download "packages" of CGI's in legible format
	The configuration templates that the Quadro uses for the IP Phones can now be modified.
	Ability to remotely access the Auto Attendant and use the admin login menu (*75) to update the AA greeting messages. Previously this login was only accessible from an extension.
	Capability to configure emergency numbers from the VoIP Carrier Wizard
	Support for multiple extensions adding to quickly and easily configure the system
5.0.19	Distinctive ringing, intercom and paging support for Polycom IP phones
5.0.17	
5.0.16	Random call hunting
	Capability to choose GUI desired theme in login
	Capability to Show/Hide extensions attached to disabled IP lines in the Extensions Management
	Capability to Show/Hide the disabled IP lines
	Auto configuration support for the following Linksys IP phone models: SPA941, SPA942, SPA921, SPA922
	Ability to remove the Display name of the call passing through Routing Table

Release	New Features
	<p>New Auto Attendant or extension adding process simplified</p> <p>Add mechanism for the DND and CallFwd functionality of Snom and Aastra IP phones.</p>
5.0.12	
5.0.11	<p>Ability to record voice messages from a phone that are referenced from the Auto Attendant Interactive Voice Response menu. When needed, the recordings can then be easily updated with current messages.</p> <p>Support for MS OCS and MS Exchange configuration with Quadro</p> <p>It is now possible to reboot each IP phone separately from the Quadro's GUI</p> <p>FXO diagnostics have been added to automatically adjust to the best echo cancellation settings</p> <p>Added receptionist wizard and expansion module support for Grandstream GXP2000</p> <p>Added silent VM recording option in the Voice Mail Settings</p> <p>Added Custom Profiles for Voice Mail Settings</p> <p>Programmable Keys Configuration page added in the IP Line Settings for Snom, Aastra, (except for Snom300 and Aastra51i, 9112i), Grandstream GXP2000. There is an advanced link on IP Lines page to configure the programmable buttons of each phone models for the "watching" and for the standard services like "DND" and others</p> <p>DHCP Advanced Settings added</p> <p>Extended flexibility for the Intercom feature: added PBX-Intercom call type in Call Routing wizard and 3 options to enable Intercom service</p> <p>A new checkbox called "Check with 3PCC" is added in Call Routing Wizard. When checking it will allow 3PCC application to place a hook on calls done through that rule</p> <p>Local authentication parameters are shown in Details column of Call Statistics</p> <p>"Check/Update Now" option is added in Automatic Firmware Update page</p> <p>Added SNMP status and configuration</p> <p>The results of system configuration backup & download are reflected in the system events</p> <p>Snom, Aastra and Grandstream phones automatically get rebooted when the Quadro is rebooted</p> <p>Added auto configuration support for the following Polycom IP phone models: Soundpoint IP 330, Soundpoint IP 550 and Soundpoint IP 650</p> <p>Intercom and paging support for Grandstream IP phones</p> <p>Possibility to hide/show disabled records in the call routing table</p> <p>SIP P-Asserted-Identity support for SIP calls to ISDN network</p> <p>Caller ID can be used to define the call destination in call routing table</p> <p>The "Deny reinvites" option is added for ITSPs that do not support this option.</p>

Release	New Features
	<p>Call forwarding configuration through custom Auto Attendant</p> <p>Added two stage dialing for FXS calls</p> <p>G729/G729a codec type selection is GUI configurable</p> <p>Added dependence for Server status and E1/T1 link status</p> <p>Language pack support for the IP Phones</p> <p>Extended auto configuration capabilities for the Aastra phones. For Aastra phones the "Time-zone" setting has been added to set up this parameter according to Quadro regional settings.</p> <p>Changed the Auto Attendant custom scenario to allow multiple WAV files to be uploaded all at once in a single compressed ZIP file.</p> <p>Added possibility to change the original display name in the Caller ID</p> <p>Added Kickback feature allowing not to lose the call after blind transfer</p> <p>Changed the Subscription limitations and made it configurable from generalconfig.cgi hidden page.</p>
4.1.58	
4.1.57	
4.1.52	<p>The results of system configuration backup & download are reflected in the system events</p> <p>Snom and Aastra phones automatically get rebooted when the Quadro is rebooted</p> <p>Added auto configuration support for the following IP phone models: Aastra51i, Snom370</p> <p>Added MSN selection for ISDN Point-To-Point mode</p> <p>Added ISDN BRI timeslot selection in Call Routing (for Japan ISDN)</p> <p>Adjusted timezone parameters for Venezuela according to new standards</p>
4.1.40	<p>IP phones do not lose registration after Quadro soft reboot (i.e. if the reboot is not initiated by disconnecting/reconnecting the power or pressing the reset button on the back of the Quadro)</p> <p>Possibility to upload and customize system messages (in the uploadownmessages.cgi hidden page)</p> <p>Attendant Ringing Announcement is now available both for default and custom AA scenarios and the selection is moved to the bottom in Attendant Scenario Settings page</p> <p>Possibility to change the default memory size to be allocated as a temporary storage for unified FAX message (in the extmanagement.cgi hidden page)</p> <p>The 3PCC Settings option was added under Telephony menu</p> <p>Multiedit support in Extensions Management for Codec Settings</p>
	<p>SIP Address Resetting function in the Extensions Management for restoring the default SIP settings of extensions</p>

Release	New Features																								
4.1.33	Possibility to change static, running logos, links and browser mini logo (accessible at loadlogo.cgi hidden page)																								
	Possibility to change the signaling procedure for hold process in case the "Send Hold Music to Remote Party" is enabled on the extension																								
	Added auto configuration support for the following IP phone models: Aastra53i, Aastra55i, Aastra57i, Aastra57iCT, Grandstream GXP-2000, BT-200, BT100 (not fully automatic yet), ATL Berkshire 5000, Thomson ST2030s																								
	Added PnP for the Aastra53i, Aastra55i, Aastra57i, Aastra57iCT																								
4.1.29	IP Line base capacity is changed, including new IP Line licensing. <i>The following chart compares the previous (release 4.0.4) IP line capacity to the new IP line capacity.</i>																								
	<table border="1" data-bbox="321 634 1481 793"> <thead> <tr> <th colspan="8">IP Phone Capacity Changes (FXS + IP)</th> </tr> <tr> <th>Model</th> <th>Old Base Capacity</th> <th>Expansion Options</th> <th>Max Capacity</th> <th>New Base Capacity</th> <th>Expansion 1</th> <th>Expansion 2</th> <th>New Max Capacity</th> </tr> </thead> <tbody> <tr> <td>Quadro2x</td> <td>2 + 4</td> <td>12 User Expansion</td> <td>2 + 16</td> <td>2 + 8</td> <td>8 User Expansion</td> <td>N/A</td> <td>2 + 16</td> </tr> </tbody> </table>	IP Phone Capacity Changes (FXS + IP)								Model	Old Base Capacity	Expansion Options	Max Capacity	New Base Capacity	Expansion 1	Expansion 2	New Max Capacity	Quadro2x	2 + 4	12 User Expansion	2 + 16	2 + 8	8 User Expansion	N/A	2 + 16
	IP Phone Capacity Changes (FXS + IP)																								
Model	Old Base Capacity	Expansion Options	Max Capacity	New Base Capacity	Expansion 1	Expansion 2	New Max Capacity																		
Quadro2x	2 + 4	12 User Expansion	2 + 16	2 + 8	8 User Expansion	N/A	2 + 16																		
4.1.22	Support of 2-stage dialing for ISDN BRI																								
	Initial VM Setup via Phone																								
4.1.18DS	Support for US new Daylight saving rules																								
4.1.18	SIP Trunk																								
	3 rd Party Call Control																								
	Flexible Numbering Plan for extensions																								
	ISDN NT Mode																								
	Download IP phone FW and Reboot of Aastra/Snom IP Phones																								
	Download Quadro Directory via XML to Snom/Aastra phones																								
	IP Phone Plug-and-Play																								
	Automatic Quadro FW update																								
	Easier GUI for forwarding lists																								
	Use 8 and 9 for extensions																								
	Kill a call from Active Calls page																								
	Detect FAX ring/voice ring for Australia																								
	Use List package for QCM/Quadro notifications																								
	Distinctive ringing on Snom and Aastra IP phones																								
Play custom message instead of ring back tone on Auto Attendant																									

Release	New Features																								
	<p>Add month/weekday to filter</p> <p>Incoming inter digit service (for E1/T1 CAS)</p> <p>Send EVENTS via SMS</p> <p>CDR Tags for Billing</p> <p>DNS/DHCP enhancement</p> <p>Daylight savings adjustment</p> <p>SMS and E-mail notification about the call forwarding</p> <p>Change extension password from phone handset</p> <p>Access to extension voice mailbox from outside by-pass the Auto Attendant</p> <p>Automatic backup and download of Quadro configuration</p>																								
4.0.4	<p>IP Line capacity changes, including new IP Line licensing</p> <p><i>The following chart compares the previous IP Phone capacities to the new IP Phone capacities.</i></p> <table border="1" data-bbox="321 1010 1484 1142"> <thead> <tr> <th colspan="8">IP Phone Capacity Changes (FXS + IP)</th> </tr> <tr> <th>Model</th> <th>3.x Base Capacity</th> <th>Expansion Options</th> <th>3.x Max Capacity</th> <th>New Base Capacity</th> <th>Expansion 1</th> <th>Expansion 2</th> <th>New Max Capacity</th> </tr> </thead> <tbody> <tr> <td>Quadro2x</td> <td>2 + 2</td> <td>4 User Expansion</td> <td>2 + 6</td> <td>2 + 4</td> <td>12 User Expansion</td> <td>N/A</td> <td>2 + 16</td> </tr> </tbody> </table> <p>OCM centralized licensing included</p>	IP Phone Capacity Changes (FXS + IP)								Model	3.x Base Capacity	Expansion Options	3.x Max Capacity	New Base Capacity	Expansion 1	Expansion 2	New Max Capacity	Quadro2x	2 + 2	4 User Expansion	2 + 6	2 + 4	12 User Expansion	N/A	2 + 16
IP Phone Capacity Changes (FXS + IP)																									
Model	3.x Base Capacity	Expansion Options	3.x Max Capacity	New Base Capacity	Expansion 1	Expansion 2	New Max Capacity																		
Quadro2x	2 + 2	4 User Expansion	2 + 6	2 + 4	12 User Expansion	N/A	2 + 16																		
3.1.21	<p>SNMP support for event monitoring</p> <p>Intercom service (for Snom, Aastra480i and Aastra480e phones)</p> <p>Paging group service (for Snom, Aastra480i and Aastra480e phones)</p> <p>Redirection on timeout to the specified address if no action on the AA welcome message</p> <p>AA welcome and menu messages enabling/disabling capability</p> <p>Call queue for virtual extensions</p> <p>Toggling for call routing entries from the handset</p> <p>Retrieve timeout configuration for parked call</p> <p>SDMF Caller ID standard</p> <p>Routing rules activity timeout</p> <p>Capability to make SIP calls using TCP as a transport protocol</p> <p>"Client Code Identification" feature on routing rule (with RADIUS enabled)</p>																								

Release	New Features
3.1.14	
3.1.7	Receptionists' Call Queue
	Extension Status Monitoring
	Call Interception
	Direct Transfer to Voicemail
	Call Park Capability on IP Phones
	Call Pickup Group
	Paging support with 3rd party devices
	Simplified IP Phone Installation (auto configuration for certain IP phones)
	Administrator Rights Management
	Support for an External Voicemail System
	Empty Voicemail Truncation
	QuadroFXO Auto Configuration
	Proprietary method for Remote Extension to bypass certain types of NAT (Symmetric RTP)
	Status for Registered IP Lines and Remote Extensions
	Readable Transfer statistics
	New voice mail notifications via phone and via SMS
Universal extension recording (music on hold, VM greetings, incoming/outgoing blocking messages)	
Sending unified fax message from mailbox to fax machine	

4 Changed Features History

The following table provides a high-level list of changed features that have been changed beginning with the most recent Quadro2x release.

Release	Changed Features
5.2.9	Changed the behavior of intercom and paging to not interrupt current active call by default
	Intercom option has been changed so that an audible sound is now provided to the called phone to alert the person when the microphone is opened.
	Indication of BLF/MWI subscription count and raising an event if the upper limit is reached
	Allowing to have multiple recording sessions regardless of the "max mail/recording duration" setting on the VM/recording box
	FTP retransmission mechanism improvement and manual FTP upload request from WebGUI. Call recordings can be manually uploaded from Web GUI.
5.1.39	
5.1.38	The SIP server value for Broadvox in the VoIP Carrier Wizard was changed
	Added an option in the Automatically Download Call Statistic page to choose the download format
	The VM-to-email text for FAX mail was changed to be different from the one of the regular voicemail text
	An audible sound to the called phone is provided in case of intercom call
5.1.31	In the call statistics-automatically download page a new option added to select the file format to download
	Added possibility to correct TX/RX gains for Aastra phones from configuration templates
5.1.27	After using the feature code *79 (for outgoing call blocking) from phone handset to block a dialed number the "Send Message to Caller Party " option should be enabled automatically
	The limitation for the number of entries in the local AAA table has been eliminated
5.1.19	
5.1.18	Added new VoIP carriers to the VoIP Carrier Wizard list (Acf2i and babyTEL)
	The "Automatic Firmware Update" link is moved from "Configuration Management" to "Firmware update" page
	The auto-configuration and PnP support are added for Polycom SoundStation IP 6000
	The auto-configuration support is added for Yealink T28 IP phone
5.1.17	Added new VoIP carriers to the VoIP Carrier Wizard list
	Adding extensions to Paging and Call Pickup groups has been simplified
	The expiration date for trial keys are shown under the Features menu
	The Call Routing Management option for the Auto Attendant has been changed from *7 to *77. This option allows entries in the Call Routing Table to be remotely enabled/disabled.

Release	Changed Features
	<p>Possibility to multi-edit the some of the extension's Voice Mailbox Settings</p> <p>A prefix is added to the Caller ID to identify calls returned by the Kickback option</p> <p>It is possible to upload the Call Queue messages as Universal Extension Recordings</p> <p>The timeout for automatic Call Back feature is changed. To activate automatic Call Back the PSTN callers should disconnect the call not after the two rings as previously, but just after one.</p> <p>The "MAC address" widget behavior is changed to be like IP address widget: if user presses 2 digits/letters, the cursor moves to the next text field.</p>
5.0.19	
5.0.17	
5.0.16	In the System-> IP routing Configuration the name of "VPN Routes" changed to "PPTP/L2TP Routes"
5.0.12	
5.0.11	<p>For Snom phones, the "Call join on Xfer (2 calls)" setting is configurable in the phone GUI</p> <p>Adjusted timezone parameters for Venezuela according to new standards</p> <p>Added status info in 3PCC settings</p> <p>Added scrollbars in the tables for Call Routing and Extension Management pages</p>
4.1.58	
4.1.57	Changed the tone detection mechanism to resolve FXO disconnect problems in South Africa
4.1.52	<p>The minimum value of SIP Registration Timeout parameter for IP lines is limited to 120 seconds. For more details see Technical Advisory chapter.</p> <p>The memory used by "DSP Capture", "Call Capture" and "Network Capture" hidden pages is limited to 3 Mb. This will put a limitation on the duration of captured file</p> <p>The maximum length of VM sent by email is limited to 3 minutes</p> <p>The no-answer timeout range for extensions is increased to 180 seconds</p> <p>The maximum count for allowed MSN numbers is increased from 10 to 16</p> <p>The number of VMs in the mailbox for one extension is limited to 300</p> <p>The firmware version control for IP lines is forcefully disabled to avoid problems on the phone during FW upgrade. If user is sure he needs that, he should re-enable that after upgrade</p> <p>Use Session Timer in IP Line Settings is deselected by default</p>
4.1.40	<p>SNMP is disabled in default configuration</p> <p>Call bandwidth usage statistics is temporarily removed</p> <p>The Call Park feature has been changed so that pressing the pound key (#) is no longer required if a password has not been assigned to the CP Extension</p>

Release	Changed Features
	<p>IP line status and SIP registration status are shown in separate pages under Quadro Status</p> <p>The "SIP Tunnels to Slave Devices" and "SIP Tunnels to Master Devices" shown under Quadro status only if there is at least one SIP tunnel active of the corresponding type</p> <p>The "SIP Trunk" is renamed to "SIP Tunnel"</p> <p>Increased the logs capacity of the Quadro by archived logging</p> <p>The echo cancellation parameters for ISDN trunks are optimized: the default values for NLP Difference and NLP Shift are set to 6 dB and 3 dB accordingly (in the trunkecho.cgi hidden page)</p> <p>New Zealand Daylight Savings Changed</p> <p>The default domain name "epyki-config.com" replaced with "epyki-config.loc"</p> <p>ISDN wizard improved</p> <p>The default registration timeout for all IP phones is set to 1 hour</p> <p>Telephone Event Draft Support checkbox removed from RTP Settings</p>
4.1.33	Best Matching Algorithm is modified
4.1.29	
4.1.22	Two new IP-PSTN providers in the "VoIP Carrier Wizard" list (AGN and Netlogic)
4.1.18DS	
4.1.18	Backup and Restore configuration procedure changed
	Download and Upload Legible configuration procedure changed
4.0.4	
3.1.21	Call back through call routing and IP/IP-PSTN implemented
	SMS settings redesigned allowing providers different from Clickatel
3.1.7	Hunt Group Changes
	Extensions Management –GUI is enhanced
	VoIP Carriers Wizard Pre-configured Carriers list expanded

5 Fixed Issues

Issues fixed since version 5.1.39:

Expansion Module's page for snom 320 is empty in the Receptionist Wizard		16142
D:	The expansion module's page of Receptionist Phone Configuration Wizard is empty and not showing the functional key configuration fields for snom320	
C:		
The firmware version control fails to change the firmware on Aastra phones		16369
D:		
C:		
Call fails when calling from an IP phone to the Aastra6731i in the paging group		16294
D:	If Aastra6731i IP phone is on a call and someone calls to the paging group, the call is put on hold and can't be retrieved.	
C:		
Extension watching stops functioning on a receptionist phone after running system configuration wizard		14828
D:		
C:		
The online help for the call statistics is missing for user login		16117
D:		
C:		

6 Known Issues

D: Description

C: Consequences

Fix: How to avoid the situation, or what to do in case the situation has occurred.

It is impossible to login as 'admin' after making changes on "Advanced PPP Settings" page 9549	
D:	You cannot login to the Quadro as 'admin' after making changes on the "Advanced PPP Settings" page. You can only login as 'user'.
C:	No consequences
F:	Restart the Quadro to resolve this.
One way audio with IPsec VPN in the scenario "Gateway<->Remote Subnet" 9327	
D:	Scenario: <ol style="list-style-type: none"> 1. Establish an IP-Sec connection between two Quadros (connection type is "Quadro <-> Remote Subnet"). 2. Make an SIP call from Quadro1 (gateway) to Quadro2 (remote subnet).
C:	The call is established, but there is no audio in Quadro1. The same result will occur when calling from Quadro2 to Quadro1. A direct call cannot be established at all.
F:	Add an additional "Quadro <> Remote Gateway" tunnel in IPsec configuration. With two tunnels: "Quadro <> Remote Gateway", "Quadro <> Remote Subnet" in IPsec VPN configuration this issue will resolved.
Call interception fails in a specific scenario with a watched extension in the many extension ring list 9399	
D:	Scenario: <ol style="list-style-type: none"> 1. Use snom360 for receptionist extension (for example, extension #31), 2. Configure Many Extension Ringing on ext. #31 with extensions #31 and #12 in the MER list, 3. Configure extensions #11 and #12 as watched extensions, 4. Make a call to extension #31, 5. The phones for extensions # 31 and #12 will start ringing. 6. The programmable key for the ext. #12 is flashing on the receptionist's ext. #31, 7. Pressing that key the receptionist stops ringing, but ext. #12 is still ringing, 8. Hang-up the phone for that caller's extension.
C:	Call interception on the receptionist's line fails. The light for ext. #11 will stay ON on the ext. #31.
F:	This problem is specific for snom phones only. When using a snom phone, calls should be answered on your own extension and not the watched extension.
Firmware update cannot be completed when "High availability" is enabled in SIP Settings page 12306	
D:	Scenario: <ol style="list-style-type: none"> 1. Using SIP Timers radio button in Telephony-SIP Settings, define the timeouts of the SIP messages retransmission as "High availability". 2. Try to make firmware update.
C:	Firmware update will hang and not complete
F:	Set the SIP Timer to RFC3261 standard before firmware update. Under investigation, will be fixed in the future releases.

An issue with configuring IP phones as local extensions for Quadro IP PBX	
13471	
D:	Plug and Play and Auto configuration of IP phones is impossible with the modified "HTTP Server Port" on the Quadro.
C:	
F:	Add the changed http port value in the "option tftp-server-name" row ("dhcpd.conf.lan" file) for each IP phone. Example: "option tftp-server-name "http://172.30.38.1:8080". Will be fixed in the future releases.
"Name recording" from Admin Login (*75) does not apply to the entries in the "Extensions Directory"	
13454	
D:	
C:	No consequences
F:	Upload user names for extensions one by one.
Some of the Quadro voice mail services could be unavailable if external Voice Mail is in use for extension	
12190	
D:	In this scenario some of the features, for example Zero-out and entering the VMS directly with option "1" will not work.
C:	
F:	This is normal, as those features are the Quadro's internal VMS system features. If external VMS system is used, user gets the features of that external system.
snom, Aastra, Grandstream and Thomson IP phones may disconnect if you press "Mute" button for a long time (60 min)	
D:	
C:	
F:	Under investigation, will be fixed in the future releases.
Aastra IP phone is not ringing when it is used in many extension ringing list	
13830	
	Scenario: <ol style="list-style-type: none"> 1. Many extension ringing is enabled on a virtual extension with an Aastra phone in the list 2. Distinctive Ringing is enabled on that virtual extension with Nickname that contains space
C:	When a call without Caller ID comes to that extension, the Aastra phone in MER does not ring.
F:	The problem is solved if there is a Caller ID available on the incoming call or if the Nickname doesn't contain a space. This problem is limited to Aastra IP phones only.
An issue with configuring Aastra IP phones as local extensions for Quadro IP PBX	
13802	
D:	After changing the LAN IP address for the Quadro the 480i, 9133i and 55i Aastra phones with currently recommended 1.4.1.2000 firmware are not registering after restart.
C:	
F:	They must be factory reset to register again. Under investigation. Will be fixed in the future FW versions for Aastra phones.
An issue with distinctive ringing on the snom and Aastra IP phones	
11519	
D:	snom and Aastra phones ring only once if the distinctive ringing is enabled with the "winter" ringing pattern.
C:	No consequences
F:	Use other ringing patterns for distinctive ringing.

Call Interception doesn't work on GrandStream GXP2000 configured as receptionist, when extensions watched on expansion module		14797
D:		
C:		
F:	Use basic 7 keys instead of expansion module. Will be fixed in the future releases.	
Paging and intercom services do not work on the GrandStream BT100 IP phone		14909
D:		
C:		
F:	Currently BT100 has no support for paging/intercom.	
It is impossible to pickup (via pickup group or extension watching) the call to extension with Find Me/Follow Me enabled		15942
D:		
C:		
F:	Will be fixed in the next releases.	
Shared mailbox users don't get new VM notifications		16047
D:	Extensions sharing the mailbox don't get notifications (both MWI and BLF) about new mails arriving to the mailbox	
C:		
F:	Will be fixed in the next releases.	
Any change in the Quadro LAN IP configuration makes it impossible to use the auto configuration for supported IP Phones		16037
D:	Changing the LAN IP or Subnet Mask in Quadro LAN IP configuration makes it impossible to use auto configuration for supported IP Phones	
C:		
F:	Discard the changes to resolve this issue. Will be fixed in the next releases.	
An issue with the Emergency Interrupt feature on snom IP phones		16391
D:	The Emergency Interrupt fails when Snom phone is in a 3-way call. Instead of ringing the phone call goes to VM directly	
C:		
F:	Will be fixed in the next releases.	
A problem with "Remove VM On Send" option in Voice mail settings		16432
D:	If this option is enabled new VMs are removed from the extension mailbox even if sending the new VM via e-mail fails because the mail server is unreachable or mail address is incorrect	
C:		
F:	Will be fixed in the next releases.	

7 Upgrading Instructions

In general, the configuration of a system will remain after the software update.

7.1 Technical Advisory

Attention: For manually configured IP phones, it is now required to have the **SIP Registration Timeout** parameter set to 120 seconds or more on your IP phone. Values less than 120 seconds will not be accepted by the Quadro and will cause the IP phone registration failure on the Quadro.

7.2 Quadro SW and HW requirements for upgrading to 5.2

Attention: The software upgrade to 5.2.x can **ONLY** be done from 5.1.38 and higher 5.1 versions. Before updating to 5.2.9 the unit should be updated to 5.1.38 or higher 5.1 version first.

Attention: The 5.2.x software can be used on almost all Quadro2x units. The exception to this is for older Quadro2x models that have only 32MB of NAND flash memory.

The following hardware versions support 5.2.x:

SASY-MICRO-0101-0002, SASY-MICRO-0101-0101, SASY-MICRO-0102-xxxx, SASY-MICRO-0103-xxxx

Note: The SASY number is found on the bottom of the unit.

Beginning with 5.1.38 software the size of NAND flash memory is also displayed within the Quadro GUI under System/Status/HW Status page. Only units that indicate 64MB of "NAND Flash" size can install 5.2.x.

Note: For units with 32MB of NAND Flash an error message is provided after an unsuccessful attempt to install 5.2. The unit will need to be rebooted at this point to recover the system.

7.3 General hints

It is recommended to execute the update by downloading the software first to a PC located in the LAN of the Quadro and perform the firmware update from the LAN side. This is to ensure that the Internet connection will not affect the upgrade process.

Additionally, it is recommended to backup the existing configuration prior to upgrading.

Remember that some data is lost during upgrade:

- **Call Statistics**
Workaround - to save the existing call statistics, download it to the PC from Call Statistics-Statistics Settings before performing the firmware update.
- **Voice mails**
Workaround – save the recorded voice mails from the Voice Mailbox before performing the firmware update.
- **All custom voice greetings**
Workaround – backup and download all configuration and voice data to a PC.
- **All custom recordings for the custom Auto Attendant**
Workaround – backup and download all configuration and voice data to a PC
- **Transfer statistics for the network**
- **Event log**
- **DHCP leases**